




Questions?

For customer service please call us at 1-310-787-1100
Office Hours: 8:00 a.m. – 5:00 p.m. PST Monday-Friday
E-mail: info@eurilighting.com



**LED Traditional
Wall Pack**

PLEASE REVIEW THE INSTRUCTIONS AND WARNINGS LISTED BELOW PRIOR TO PROPER INSTALLATION

WARNINGS	IMPORTANT
<ul style="list-style-type: none"> • Do not use the electric generator to test the LED lamp. • Please abide by related country, regional and local law and regulations when installing this fixture. • Please turn off the power before installation or maintenance. • Proper grounding is required to ensure safety. 	<ul style="list-style-type: none"> • To avoid possibility of electrical shock or fire, the installation personnel must have professional electric knowledge. • Please wear gloves to avoid injury before installation. • If smoke or fire is found in wires or led fixture during or after installation, please turn off the power immediately and notify relevant personnel. • This fixture is available in outdoor usage, but the distance from fixture to ground should be more than 2m.
<p>Warning/ Avertissement MIN 90°C SUPPLY CONDUCTOR. THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED.</p>	

APPLICATIONS

Tunnel (except for motor vehicle tunnel), workshop, warehouse, factory, house, building exterior, etc.

INSTALLATION INSTRUCTIONS

This installation instruction applies to the following products. Although the products vary in appearance, their installation steps are the same


INSTALLATION (1)




1 Turn off the power.




2 Use a screwdriver to remove the screws on both sides.




3 Open the fixture, disconnect the connection terminals, and remove the upper cover of the fixture.




4 Use a screwdriver to remove the plug.




5 Drill through the mounting hole with an electric drill.




6 Attach EVA cotton pad to bottom shell.




7 Thread the wire through the bottom hole.



8 Lock the bottom shell on the mounting seat with screws.




9 L, N and G wires connected to the power supply.



10 Install the cover of the fixture and connect the terminal block.



11 Fix the fixture with screws.




12 Make sure the installation is complete before turning on the power switch.



Questions?

For customer service please call us at 1-310-787-1100
Office Hours: 8:00 a.m. – 5:00 p.m. PST Monday-Friday
E-mail: info@eurilighting.com




LED Traditional Wall Pack

PLEASE REVIEW THE INSTRUCTIONS AND WARNINGS LISTED BELOW PRIOR TO PROPER INSTALLATION


INSTALLATION (2)




1 Turn off the power.




2 Use a screwdriver to remove the screws on both sides.




3 Open the fixture, disconnect the connection terminals, and remove the upper cover of the fixture.




4 Drill through the mounting hole with an electric drill.




5 Drill a hole in the wall with an electric drill.




6 Push the expansion rubber plug into the mounting hole on the wall.




7 Use a screwdriver to remove the side plug and attach the EVA cotton pad to the mounting hole.




8 Push the expansion rubber plug into the mounting hole on the wall




9 The top terminal connect the wire tube through the side hole to the L,N and G wires on the power supply.



10 Install the upper cover of the fixture and connect the terminal line.



11 Fix the fixture with screws.



12 Make sure the installation is complete before turning on the power switch.

STANDARD WIRE

L/live wire: Black\Brown; N/null wire: White\Blue; Ground wire: Green\Yellow-green. Warning: During grounding, make sure the earth wire of the driver and fixture housing are connected together with the earth wire of the local power supply.

RECOMMENDED DIMMER LIST

LUTON: NTSTV-DV
LEVITON: DS710-10Z
LEVITON: IP710
Legrand: RH4FBL3PW